


307

Mid Tower

User Manual





Product Story

The 300 series maintains its distinguished, simple and clean appearance, which emphasizes the quality of the materials. But, the new 307 chassis brings a fresh new design concept to add and enhance to the classic appearance of the 300 series. The RGB LEDs are rich and saturated with colors to provide an all new experience! The 307's built-in microphone integrates with the environment and reacts accordingly. A total of 12 lighting modes are accommodated with GLOW, the exclusive LED software. Users are free to design their dream front panel and use it in creative and customizable ways to suit their desires. Master your creativity.

Specification

Model	307
Color	White
Case Type	Mid Tower
Material	SECC, Tempered Glass
M/B Compatibility	12" x 10.7" ATX, Micro-ATX, Mini-ITX
Expansion Slots	PCI-E x 7
Maximum Compatibility	VGA Card Length: 350mm CPU Heatsink Height: 160mm
Front Ports	1 X USB 3.1 Gen 2 Type-C 2 x USB 3.0 LED Mode Button HD Audio
Internal Drive Bays	2 x 3.5" 2 x 2.5" 2 Pre-installed (Max. up to 3 bays)
Thermal Solution Compatibility	1 x 120mm Rear Fan / 120mm Radiator 3 x 120mm Top Fan / 360mm Radiator 3 x 120mm Bottom Fan
Power Supply Compatibility	PSII : ATX12V - Length up to 200mm
Product Dimension (H x W x D)	480mm x 215mm x 480mm 18.8" x 8.4" x 18.8"
Product Dimension with screw & handle height (H x W x D)	532mm x 240mm x 501mm 20.9" x 9.4" x 19.7"
Package Dimension (H x W x D)	335mm x 610mm x 624mm 13.1" x 24" x 24.5"
Net Weight	11.61kg / 25.5lb
Gross Weight	14.06kg / 30.9lb

* Our products comply with RoHS regulation

* Specifications may vary based on different regions


* Pre-installed glass panel. Extra fee for close panel.

307

Package Content



1 307 Chassis



2 QR Code Card




3 Accessories Bag

Accessories Bag

**X7****A** Motherboard Stand-off**X1****B** Motherboard Stand-off Socket**X18****C** Hexagon Head Screws**X18****D** 2.5" HDD Screws**X10****E** 3.5" HDD Screws**X10****F** Cable Tie**X8****G** Water-cooling System Washer**X1****H** Graphics Card Holder

Case Structure



- 1 Power Button
- 2 Power LED Indicator
- 3 USB 3.0 Ports
- 4 USB 3.1 Gen 2 Type-C Port
- 5 Audio Ports
(Earphone and Microphone)
- 6 Reset Button
- 7 LED Mode Button
- 8 LED Light Button

Case Structure



- 9** 3.5" Drive Bay
- 10** 2.5" Drive Bay
- 11** Top Fan/ Radiator Mounting Area
- 12** Rear Fan/ Radiator Mounting Area
- 13** Bottom Fan Mounting Area
- 14** Motherboard Mounting Area
- 15** PCI-E Expansion Slot
- 16** Extra PCI-E Supporting Mounting Hole
- 17** Power Supply Mounting Area
- 18** Fan Dust Filter
- 19** Shock-Proof Stand

Installation Guide

1 Opening the Chassis

Please remove by pressing the handle on top of panel.



2 Power Supply Installation

Please pull out the insulating paper.



Installation Guide

3 Power Supply Installation

Parts Required: Hexagon Head Screws

Power supply can be mounted on the top bracket



4 Motherboard Installation


Parts Required: Motherboard Stand-Off, Motherboard Stand-Off Socket, Motherboard Screws




Installation Guide

5 Expansion Card Installation

Parts Required: Hexagon Head Screws, Graphics Card Holder









6.a I/O Wires Installation




Installation Guide

6.b HD Audio Header

PORT2_2	Blue	10		9	Brown	SENCE2_R
SENSE_SEND	Purple	8		7		Key
PORT2_R	Yellow	6		5	Green	SENSE1_R
PORT1_R	White	4		3	Orange	PRESENCE#
PORT1_L	Red	2		1	Black	GND




6.c USB3.0 Header




Installation Guide

6.d Type-C Cable




6.e LED Pipe Power

Ensure the beveled edge of the PSU connector is properly aligned with the beveled edge of the LED light connector



Installation Guide

- 6.f** USB-Strip
Please plug in USB port on motherboard.



- 7** 2.5" Drive Bays Installation
Parts Required: 2.5" HDD Screws



Installation Guide

8 3.5" Drive Bays Installation

Parts Required: 3.5" HDD Screws



9 Fan / Liquid Cooling Radiator Installation

Parts Required: Water-cooling System Washer



Installation Guide

10 Completing Installation

Parts Required: Cable Ties






GLOW Software Instructions

The InWin exclusive GLOW software encourages users to create their own unique lighting effect. Choose your own style! The simple and clean intuitive interface is easy to operate. GLOW possesses 12 different lighting modes, but the most intriguing is Creation Mode, which grants users access to design their own front panel to match their preferred theme. The only limitation is your own imagination!

- 1** Please click "download" on 307 website to install the GLOW software.
- 2** After downloading the GLOW on the desktop, please click to open it.



GLOW Software Instructions



Mode descriptions:




Night Light
Create an atmosphere in dark room



Candle
Lighting effect by voice catching from microphone



Sky
Cloud floating in sky



Music
Equalizer mode's lights reveal the rhythm of music



Vortex
Rotating vortex



Twinkling
Like stars twinkling in night sky



Time Tunnel
Dazzling tunnel effect



E.C.G
Heartbeat effect by voice catching from microphone



Bounce
Light moves like bouncing ball



Time
Clock display the time




Hourglass
Double click to set the time, maximum 60min. Clap hand to reset the time when red flash light shows time up.



Creation
Customize own lighting effect

GLOW Software Instructions




Colors:

Each mode provide 3 color to choose, except Candle Mode.

Lights & Speed:


Control lights and speed by + and - by buttons, there have 7 levels.

GLOW Software Instructions



MIC threshold settings
For candle, E.C.G & hourglass mode.


Threshold1: (0 - 4095)

* Threshold2: (0 - 4095)
* Also for countdown triggering of hourglass mode.

Threshold3: (0 - 4095)

Threshold4: (0 - 4095)

Countdown for (1-60) **Minutes**
For hourglass mode.

Audio source: 
For music mode.

Buttons: Restore default, Save to ROM, Apply


MIC threshold settings:

Please adjust the setting from small number.

Hourglass time setting:

Please setting from 1 to 60 minutes.

GLOW Creation Mode



Brush



Eraser



File




Painting




Trash Can



Save



Palette



SlideShow:

Provide 4 plates to create image, which offer 60 second maximum to setting slideshow time on front panel.



CONTEMPORARY & INNOVATIVE
w w w . i n - w i n . c o m